



ELECTRONICS, INC.

44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089

<http://www.nteinc.com>

## NTE2056 Integrated Circuit 8-Bit Multiplying Digital-to-Analog Converter

### Description:

The NTE2056 is an 8-bit multiplying D-to-A converter in a 16-Lead DIP type package designed for use where the output current is a linear product of an eight-bit digital word and an analog input voltage.

### Features:

- Fast Setting Time: 300ns Typ
- Non-Inverting Digital Inputs are MTTL and CMOS Compatible
- Output Voltage Swing: +0.4V to -5.0V
- High-Speed Multiplying Input: Slew Rate 4.0mA/μs
- Standard Supply Voltages: +5.0V and -5.0V to -15V

### Applications:

- |   |  |
|---|--|
| <ul style="list-style-type: none"> <li>● Tracking A-to-D Converters</li> <li>● Successive Approximation A-to-D Converters</li> <li>● 2 1/2 Digit Panel Meters and DVM's</li> <li>● Waveform Synthesis</li> <li>● Sample and Hold</li> <li>● Peak Detector</li> <li>● Programmable Gain and Attenuation</li> <li>● CRT Character Generation</li> </ul> | <ul style="list-style-type: none"> <li>● Audio Digitizing and Decoding</li> <li>● Programmable Power Supplies</li> <li>● Analog-Digital Multiplication</li> <li>● Digital-Digital Multiplication</li> <li>● Analog-Digital Division</li> <li>● Digital Addition and Subtraction</li> <li>● Speech Compression and Expansion</li> <li>● Stepping Motor Drive</li> </ul> |
|---|--|

### Absolute Maximum Ratings: (T<sub>A</sub> = +25°C unless otherwise specified)

Power Supply Voltage

V <sub>CC</sub> .....	+5.5V
V <sub>EE</sub> .....	-16.5V
Digital Input Voltage, V <sub>5</sub> thru V <sub>12</sub> .....	0 to +5.5V
Applied Output Voltage, V <sub>O</sub> .....	+0.5V, -5.2V
Reference Current, I <sub>14</sub> .....	5mA
Reference Amplifier Inputs	
V <sub>14</sub> .....	V <sub>CC</sub>
V <sub>15</sub> .....	V <sub>EE</sub>
Operating Temperature Range, T <sub>A</sub> .....	0° to +75°C
Storage Temperature Range, T <sub>stg</sub> .....	-65° to +150°C

**Electrical Characteristics:** ( $T_A = 0^\circ$  to  $+75^\circ\text{C}$ ,  $V_{CC} = +5\text{V}$ ,  $V_{EE} = -15\text{V}$ ,  $V_{ref}/R14 = 2\text{mA}$ , All digital inputs at high logic level, unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Relative Accuracy (Error relative to full scale $I_O$ )	$E_r$	Note 1	-	-	$\pm 0.78$	%
Setting Time to within $\pm 1/2$ LSB (Includes $t_{PLH}$ )	$t_S$	$T_A = +25^\circ\text{C}$ , Note 2	-	300	-	ns
Propagation Delay Time	$t_{PLH}$ , $t_{PHL}$	$T_A = +25^\circ\text{C}$	-	30	100	ns
Output Full Scale Current Drift	$TCI_O$		-	-20	-	PPM/ $^\circ\text{C}$
Digital Input Logic Levels (MSB) High Level, Logic "1"	$V_{IH}$		2.0	-	-	V
Low Level, Logic "0"	$V_{IL}$		-	-	0.8	V
Digital Input Current (MSB) High Level	$I_{IH}$	$V_{IH} = 5\text{V}$	-	0	0.04	mA
Low Level	$I_{IL}$	$V_{IL} = 0.8\text{V}$	-	-0.4	-0.8	mA
Reference Input Bias Current (Pin15)	$I_{15}$		-	-1.0	-5.0	$\mu\text{A}$
Output Current Range	$I_{OR}$	$V_{EE} = -5\text{V}$	0	2.0	2.1	mA
		$V_{EE} = -15\text{V}$ , $T_A = +25^\circ\text{C}$	0	2.0	4.2	mA
Output Current	$I_O$	$V_{ref} = 2.000\text{V}$ , $R14 = 1000\Omega$	1.9	1.99	2.1	mA
	$I_{O (min)}$	All bits low	-	0	4.0	$\mu\text{A}$
Output Voltage Compliance	$V_O$	$E_r \leq 0.19\%$ , $T_A = +25^\circ\text{C}$ Pin1 Grounded	-	-	-0.55, +0.4	V
		Pin1 Open, $V_{EE}$ below $-10\text{V}$	-	-	-5.0, +0.4	V
Reference Current Slew Rate	SR $I_{ref}$		-	4.0	-	mA/ $\mu\text{s}$
Output Current Power Supply Sensitivity	PSRR(-)		-	0.5	2.7	$\mu\text{A}/\text{V}$
Power Supply Current	$I_{CC}$	All bits low	-	+13.5	+22.0	mA
	$I_{EE}$		-	-7.5	-13.0	mA
Power Supply Voltage Range	$V_{CCR}$	$T_A = +25^\circ\text{C}$	+4.5	+5.0	+5.5	V
	$V_{EER}$		-4.5	-15.0	-16.5	V
Power Dissipation All bits low	$P_D$	$V_{EE} = -5\text{V}$	-	105	170	mW
		$V_{EE} = -15\text{V}$	-	190	305	mW
		$V_{EE} = -5\text{V}$	-	90	-	mW
		$V_{EE} = -15\text{V}$	-	160	-	mW
All bits high						

Note 1. All current switches are tested to guarantee at least 50% of rated output current.

Note 2. All bits switched.

### Pin Connection Diagram

