



ELECTRONICS, INC.  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## NTE350F Silicon NPN Transistor RF Power AMP

**Description:**

The NTE350F is designed for 12.5 Volt large-signal amplifier applications required in commercial and industrial equipment operating to 300MHz.

**Features:**

- Specified 12.5 Volt, 175MHz Characteristics:  
     Output Power = 15 Watts  
     Minimum Gain = 6.3dB  
     Efficiency = 60%
- Characterized with Series Equivalent Large-Signal Impedance Parameters

**Absolute Maximum Ratings:**

Collector-Emitter Voltage, $V_{CEO}$ .....	18V
Collector-Base Voltage, $V_{CB}$ .....	36V
Emitter-Base Voltage, $V_{EB}$ .....	4V
Collector Current, $I_C$ .....	2.5A
Total Device Dissipation, $P_D$	
$T_C = +25^\circ\text{C}$ (Note 1) .....	31W
Derate above $+25^\circ\text{C}$ .....	177W/ $^\circ\text{C}$
Storage Temperature Range, $T_{stg}$ .....	$-65^\circ$ to $+200^\circ\text{C}$

Note 1. Device is designed for RF operation. The total dissipation rating applies only when the devices are operated as RF amplifiers.

**Electrical Characteristics:** ( $T_C = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
<b>OFF Characteristics</b>						
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C = 20\text{mA}, I_B = 0$	18	-	-	V
	$V_{(BR)CES}$	$I_C = 10\text{mA}, V_{BE} = 0$	36	-	-	V
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	$I_E = 2.0\text{mA}, I_C = 0$	4.0	-	-	V
Collector Cutoff Current	$I_{CES}$	$V_{CE} = 15\text{V}, V_{BE} = 0, T_C = +55^\circ\text{C}$	-	-	8.0	mA
	$I_{CBO}$	$V_{CB} = 15\text{V}, I_E = 0$	-	-	0.5	mA
<b>ON Characteristics</b>						
DC Current Gain	$h_{FE}$	$I_C = 0.5\text{A}, V_{CE} = 5.0\text{V}$	5.0	-	-	
<b>Dynamic Characteristics</b>						
Output Capacitance	$C_{ob}$	$V_{CB} = 15\text{V}, I_E = 0, f = 0.1\text{MHz}$	-	70	85	pF
<b>Functional Test</b>						
Common-Emitter Amplifier Gain	$G_{PE}$	$P_{OUT} = 15\text{W}, V_{CC} = 12.5\text{V}, f = 175\text{MHz}$	6.3	-	-	dB
Collector Efficiency	$\eta$	$P_{OUT} = 15\text{W}, V_{CC} = 12.5\text{V}, f = 175\text{MHz}$	60	-	-	%

