

TRANSISTOR NUMBER	PM OAL T	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
BF177	NS	T039	L04	100V	60V	5V	50MA	200C	600MWF	60M	3R6	20MN	10MA	TVM	MUB	BF179C		0
BF178	NS	T039	L04	185V	115V	5V	50MA	200C	600MWF	60M	3R6	20MN	15MA	TVM	MUB	BF179C		0
BF179	NS	T039	L04	250V	115V	5V	50MA	200C	600MWF	60M	3R6	20MN	20MA	TVH	MUB	BF179C		0
BF179A	NS	T039	L04	160V	115V	5V	50MA	200C	600MWF	60M	3R5	20MN	30MA	TVE	MUB	BF179C		0
BF179B	NS	T039	L04	220V	115V	5V	50MA	200C	600MWF	60M	3R5	20MN	30MA	TVE	MUB	BF179C		0
BF179C	NS	T039	L04	250V	115V	5V	50MA	200C	600MWF	60M	3R5	20MN	30MA	TVE	MUB	BF179C		0
BF180	NS	T072	L06	30V	20V	3V	20MA	175C	150MWF	335M	DR56	13MN	2MA	TUG	MUB	BF180		0
BF181	NS	T072	L06	30V	20V	3V	20MA	175C	150MWF	300M	DR56	13MN	2MA	TUO	MUB	BF180		0
BF182	NS	T072	L06	25V	20V	3V	15MA	175C	150MWF	325M	DR66	10MN	2MA	TJM	MUB	BF182		0
BF183	NS	T072	L06	25V	20V	3V	15MA	175C	150MWF	400M	DR66	10MN	3MA	TUO	MUB	BF183		0
BF184	NS	T072	L51	30V	20V	5V	30MA	175C	145MWF	150M	1R3	75/750	1MA	FRH	MUB	BF184		0
BF185	NS	T072	L51	30V	20V	5V	30MA	175C	145MWF	110M	1R3	34/140	1MA	FRM	MUB	BF185		0
BF186	NS	T039	L04	165V		5V	50MA	200C	750MWF	60M	4P	20MN	40MA	TVH	OBS	BF178		0
BF187	NS	T018	L01	40V			25MA	175C	160MWF	250M		40MN	10MA	FVG	OBS	BF200		0
BF188	NS	T072	L06	50V	50V	5V	50MA	175C	200MWF	300M		25MN	10MA	FVG	OBS	BF200		0
BF189	NS	T072	L06	50V	30V	5V	25MA	175C	160MWF	150M		65MN	1MA	FVG	OBS	BF200		0
BF194	NS	X09	L11	30V	20V	5V	30MA	125C	250MWF	130M	1R9	67/220	1MA	FRH	MUB	BF184		0
BF195	NS	X09	L11	30V	20V	5V	30MA	125C	250MWF	100M	1R9	36/125	1MA	FRM	MUB	BF185		0
BF196	NS	X09	L11	40V	30V	4V	25MA	125C	250MWF	200M	OR4	27MN	4MA	TIG	MUB	BF167		0
BF197	NS	X09	L11	40V	20V	4V	25MA	125C	250MWF	275M	OR6	38MN	7MA	TIA	A	BF173		0
BF198	NS	X10	L19	40V	30V	4V	25MA	125C	250MWF	200M	OR4	27MN	4MA	TIG	TFK	BF167		0
BF199	NS	X10	L19	40V	20V	4V	25MA	125C	250MWF	275M	OR6	38MN	7MA	TIA	TFK	BF173		0
BF200	NS	T072	L06	30V	20V	3V	20MA	175C	150MWF	325M	DR56	15MN	2MA	FVG	MUB	BF200		0
BF206	NS	T072	L06	30V	20V	3V	20MA	175C	200MWF	250M	OR5	20MN	2MA	FVG	OBS	BF200		0
BF207	NS	T072	L06	40V	30V	4V	25MA	175C	150MWF	200M	OP3	40MN	4MA	FVG	OBS	BF200		0
BF208	NS	T072	L06	40V	25V	4V	25MA	175C	230MWF	300M	DR46	50MN	7MA	FVG	OBS	BF200		0
BF209	NS	T072	L06	30V	20V	3V	20MA	175C	200MWF	250M	OR6	15MN	2MA	FVG	OBS	BF200		0
BF212	NS	T072	L06	30V	20V	3V	20MA	175C	200MWF	350M	OR5	22MN	2MA	FVG	OBS	BF200		0
BF213	NS	T072	L06	20V	15V	3V	50MA	175C	200MWF	300M	OR6	15MN	2MA	TUH	OBS	BF180		0
BF214	NS	T072	L51	30V	30V	4V	30MA	175C	160MWF	150M	OP7	75MN	1MA	FRH	OBS	BF184		0
BF215	NS	T072	L51	30V	30V	4V	30MA	175C	160MWF	150M	OP7	35MN	1MA	FRM	OBS	BF185		0
BF216	NS	T098	L21	35V	35V	5V	20MA	125C	120MWF	100M	1R3	50MN	1MA	RLA	OBS	BF369	2N3856	2
BF217	NS	T098	L21	35V	35V	5V	20MA	125C	120MWF	120M	1R3	75MN	1MA	RLA	OBS	BF369	2N3856	2
BF218	NS	T098	L21	35V	35V	5V	20MA	125C	120MWF	110M	1R3	50MN	1MA	RLA	OBS	BF369	2N3856	2
BF219	NS	T098	L21	35V	35V	5V	20MA	125C	120MWF	130M	1R3	75MN	1MN	RLA	OBS	BF369	2N3856	2
BF220	NS	T098	L21	35V	35V	5V	20MA	125C	120MWF	130M	1R3	50MN	1MA	RLA	OBS	BF369	2N3856	2
BF221	NS	T018	L01	30V	30V	6V	100MA	185C	300MWF	70M	5P6	20MN	10MA	RLA	OBS	BF759	2N3946	2
BF222	NS	T072	L06	50V	50V	4V	20MA	175C	175MWF	200M		20MN	2MA	FVG	SGI	BF200		0
BF223	NS	X09	L11	32V	25V	4V	30MA	140C	350MWF	375M	OR7	40MN	15MA	TIA	TFK	BF173		0
BF224	NS	X10	L19	45V	30V	4V	50MA	150C	360MWF	300M	DR46	30MN	7MA	TIA	TIB	BF173		0
BF224J	NS	T092	L53	45V	30V	4V	50MA	150C	360MWF	300M	DR46	30MN	7MA	TIA	TIB	BF173		0
BF224JF	NS	T092	L58	45V	30V	4V	50MA	150C	360MWF	300M	DR46	30MN	7MA	TIA	TIB	BF173		0
BF225	NS	X10	L19	50V	40V	4V	50MA	150C	360MWF	400M	DR44	30MN	4MA	TIG	TIB	BF167		0
BF225J	NS	T092	L53	50V	40V	4V	50MA	150C	360MWF	400M	DR44	30MN	4MA	TIG	TIB	BF167		0
BF225JF	NS	T092	L58	50V	40V	4V	50MA	150C	360MWF	400M	DR44	30MN	4MA	TIG	TIB	BF167		0
BF226	NS	T072	L51	30V	30V	4V	50MA	175C	165MWF	150M	1R4	34/165	1MA	FRM	SES	BF185		0
BF227	NS	X25	L56	40V	25V	4V	25MA	125C	50MWF	300M	DR46	30MN	3MA	TIA	TFK	BF173		0
BF228	NS	X25	L55	100V	80V	7V	50MA	125C	50MWF	50M		30MN	2MA	ALH	TFK	BSX21	2N1990R	0
BF229	NS	X25	L56	30V	20V	5V	30MA	125C	50MWF	130M	1R7	67/220	1MA	FRH	TFK	BF184		0
BF230	NS	X25	L56	30V	20V	5V	30MA	125C	50MWF	100M	1R7	36/125	1MA	FRM	TFK	BF185		0
BF231	NS	T018	L01	15V	12V	6V	50MA	185C	300MWF	500M	1R6	20MN	4MA	ULA	OBS	BF367	2N3983	2
BF232	NS	T072	L51	25V	25V	4V	30MA	175C	270MWF	300M	DR68	30MN	7MA	TIA	SID	BF173		0
BF232	NS	T018	L01	15V	12V	6V	50MA	185C	300MWF	500M	1R6	20MN	4MA	ULA	OBS	BF367	2N3983	2
BF233	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	40/350	1MA	FRH	SES	BF184		0
BF233	NS	T018	L01	15V	12V	6V	50MA	185C	300MWF	500M	1R6	20MN	4MA	ULA	OBS	BF367	2N3983	2
BF233/2	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	40/70	1MA	FRH	SES	BF184		0
BF233/3	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	60/100	1MA	FRH	SES	BF184		0
BF233/4	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	90/150	1MA	FRH	SES	BF184		0
BF233/5	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	140MN	1MA	FRH	SES	BF184		0
BF233/6	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	200MN	1MA	FRH	SES	BF184		0
BF234	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	90/330	1MA	FRH	SGI	BF184		0
BF235	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	40/165	1MA	FRM	SES	BF185		0
BF236	NS	T0106	L18	30V	30V	4V	30MA	125C	300MWF	150M	1R0	34/165	1MA	FRM	SES	BF185		0
BF237	NS	X10	L19	45V	30V	4V	30MA	150C	360MWF		OR6	30MN	1MA	FRM	TIB	BF185		0
BF238	NS	X10	L19	45V	30V	4V	30MA	150C	360MWF		OR6	60MN	1MA	FRH	TIB	BF184		0
BF240	NS	X10	L19	40V	40V	4V	25MA	150C	300MWF	215M	DR34	67/220	1MA	TIG	TFK	BF167		0
BF240	NS	T018	L01	20V	15V	4V	100MA	175C	300MWF	90M	4P	35MN	2MA	RLA	OBS	BF185	2N3856	2
BF240B	NS	X13		40V	40V		25MA	125C	250MWF	225M	OR6	110MN	1MA	RLA	PIH	BF394B	2N3856	2
BF241	NS	X10	L19	40V	40V	4V	25MA	150C	300MWF	200M	DR34	36/125	1MA	FRM	TFK	BF167		0
BF241	NS	T018	L01	30V	30V	4V	100MA	175C	300MWF	90M	4P	60/120	2MA	RLA	OBS	BF185	2N3856	2
BF241A	NS	T018	L01	60V	60V	4V	100MA	175C	300MWF	90M	4P	60/120	2MA	RLA	OBS	BF179	2N3983	2
BF241C	NS	X13		40V	40V		25MA	125C	250MWF	200M	OR6	32MN	1MA	RLA	PIH	BF199	2N3983	2
BF241D	NS	X13		40V	40V		25MA	125C	250MWF	200M	OR6	38MN	1MA	RLA	PIH	BF199	2N3983	2
BF242	NS	T018	L01	30V	30V	4V	100MA	175C	300MWF	90M	4P	100MN	2MA	RLA	OBS	BF394A	2N3946	2
BF242A	NS	T018	L01	60V	60V	4V	100MA	175C	300MWF	90M	4P	100MN	2MA	RLA	OBS	BF394A	2N3946	2