

TRANSISTOR NUMBER	PM OAL T	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
BF243	PS	X10	L19	35V	32V	5V	50MA	150C	200MWF	80M		30MN	1MA	ALG	OBS			0
BF243	NS	T018	L01	30V	30V	4V	100MA	175C	300MWF	90M	4P	150MN	2MA	RLA	OBS	BF394A	2N3856	2
BF244	NS	T018	L01	30V	30V	4V	100MA	175C	300MWF	90M	4P	250MN	2MA	RLA	OBS	BF394A	2N3856	2
BF248	NS	T018	L01	30V	25V	3V	600MA	175C	400MWF	180M	9P	30/300	10MA	RLG	TIF	BSW64	2N2222A	0
BF249	PS	T018	L01	30V	25V	3V	600MA	175C	400MWF	180M	9P	30/300	10MA	RLG	TIF	BSW24	2N2907A	0
BF250	NS	T018	L01	15V	15V	3V	600MA	175C	400MWF	20M	10P	75MN	100UA	RLG	TIF	BC109	2N930	0
BF251	NS	T072	L51	30V	30V	4V	25MA	175C	150MWF	300M	OR3	30MN	4MA	TIG	SGI	BF167		0
BF252	NS	T072	L51	40V	30V	4V	25MA	175C	150MWF	100M	DR74	30MN	2MA	FRM	SGI	BF185		0
BF253	NS	X10	L19	30V	25V	3V	35MA	170C	280MWF	75M		50/330	1MA	RLA	SAS	BF254		1
BF254	NS	X10	L19	30V	20V	5V	30MA	150C	300MWF	130M	1R7	67/220	1MA	FRH	MUB	BF184		0
BF254B	NS	X13		30V	20V	5V	30MA	125C	180MWF	130M	1R7	110MN	1MA	RLA	PIH	BF394C	2N3856	2
BF254-3	NS	X10	L19	30V	20V	5V	100MA	150C	625MWF	130M	1R7	65MN	1MA	FRM	MOU			2
BF254-4	NS	X10	L19	30V	20V	5V	100MA	150C	625MWF	130M	1R7	100MN	1MA	FRH	MOU			2
BF255	NS	X10	L19	30V	20V	5V	30MA	150C	300MWF	100M	1R7	36/125	1MA	FRM	MUB	BF185		0
BF255	NS	T072	L06	40V	40V	4V	20MA	175C	260MWF	1400M	9P	22MN	2.5M	SLA	RIZ	BFT17	2N5835	2
BF255C	NS	X13		30V	20V	5V	30MA	125C	180MWF	100M	1R7	72MN	1MA	RLA	PIH	BF184	2N3856	2
BF255D	NS	X13		30V	20V	5V	30MA	125C	180MWF	100M	1R7	38MN	1MA	RLA	PIH	BF184	2N3856	2
BF255-2	NS	X10	L19	30V	20V	5V	100MA	150C	625MWF	100M	1R7	35MN	1MA	FRM	MOU			2
BF255-3	NS	X10	L19	30V	20V	5V	100MA	150C	625MWF	100M	1R7	65MN	1MA	FRM	MOU			2
BF257	NS	T039	L04	160V	160V	5V	100MA	175C	500MWF	55M	7P	25MN	30MA	TVM	SES	BF257		0
BF257A	NS	T039	L04	180V	180V	5V	100MA	175C	500MWF	55M	7P	25MN	30MA	RLA	TIB	BF259	2N3440	2
BF257B	NS	T039	L04	220V	220V	5V	100MA	175C	500MWF	55M	7P	25MN	30MA	RLA	TIB	BF259	2N3440	2
BF257C	NS	T039	L04	220V	220V	5V	100MA	175C	500MWF	55M	7P	25MN	30MA	RLA	TIB	BF259	2N3440	2
BF257D	NS	T039	L04	160V	160V	5V	100MA	175C	500MWF	55M	7P	30/150	30MA	RLA	TIB	BF259	2N3440	2
BF257G	NS	T039	L04	170V	170V	5V	100MA	175C	500MWF	55M	7P	25MN	30MA	RLA	TIB	BF259	2N3440	2
BF257N	NS	T039	L04	180V	180V	5V	100MA	175C	500MWF	55M	7P	25MN	30MA	RLA	TIB	BF259	2N3440	2
BF257S	NS	T039	L04	140V	140V	5V	100MA	175C	500MWF	55M	7P	25MN	30MA	RLA	TIB	BF259	2N3440	2
BF258	NS	T039	L04	250V	250V	5V	100MA	175C	800MWF	55M	7P	25MN	30MA	TVH	SES	BF258		0
BF258A	NS	T039	L04	280V	280V	5V	100MA	175C	800MWF	55M	7P	25MN	30MA	TVH	SAS	BF259	2N5058	2
BF259	NS	T039	L04	300V	300V	5V	100MA	175C	500MWF	90M	7P	25MN	30MA	VLE	SES	BF259		0
BF259A	NS	T039	L04	300V	300V	5V	200MA	175C	500MWF	90M	7P	25MN	30MA	VLE	TIB	BF259	2N5058	2
BF259G	NS	T039	L04	300V	300V	5V	200MA	175C	500MWF	90M	7P	10MN	30MA	VLE	TIB	BF259	2N5058	2
BF260	NS	T072	L51	45V	30V	4V	50MA	175C	150MWF	400M	DR32	35MN	1MA	TVG	ATI	BF200		0
BF261	NS	T072	L51	40V	30V	4V	50MA	175C	150MWF	365M	DR32	35MN	1MA	TIG	ATI	BF167		0
BF262	NS	X32	L71	30V	20V	3V	20MA	125C	120MWF	400M				ULA	RTC	BF362		1
BF263	NS	X32	L71	30V	20V	3V	20MA	125C	120MWF	525M				ULA	RTC	BF362		1
BF264	NS	X32	L71	30V	20V	3V	20MA	125C	120MWF	400M				VLA	RTC	BF480		1
BF266	NS	T072	L06	40V	40V	5V	20MA	175C	175MWF	250M	OR8	22MN	2.5MA	RLA	RIZ	BF196	2N3983	2
BF267	NS	T072	L51	30V	30V	5V	25MA	175C	130MWF	175M	OR3	27MN	4MA	RLA	RIZ	BF196	2N3983	2
BF268	NS	T018	L01	30V	30V	4V	25MA	175C	150MWF	600M		25MN		ULA	OR8	BFY90	2N2857	0
BF270	NS	T072	L06	40V	40V	4V	20MA	175C	150MWF	300M	OR2	30MN	3MA	TIG	SGI	BF167		0
BF271	NS	T072	L06	30V	30V	4V	50MA	200C	250MWF	450M		30MN	10MA	TIA	SGI	BF173		0
BF272	PS	T072	L06	45V	30V	4V	20MA	175C	150MWF	700M	OP3	25MN	3MA	ULA	ATB	BF576		1
BF272A	PS	T072	L06	40V	35V	3V	20MA	200C	200MWF	700M	OR5	25MN	3MA	ULA	ATB	BF576		1
BF273	NS	T0106	L18	25V	25V	4V	50MA	125C	200MWF	400M	OR6	35MN	1MA	TVG	SGI	BF200		0
BF273	NS	T072	L51	25V	25V	5V	25MA	175C	250MWF	275M	DR46	38MN	7MA	VLA	RIZ	BF199	2N3983	2
BF273C	NS	T0106	L18	25V	25V	4V	50MA	125C	200MWF	400M	OR6	70/120	1MA	TVG	SGI	BF200		0
BF273D	NS	T0106	L18	25V	25V	4V	50MA	125C	200MWF	400M	OR6	35/75	1MA	TVG	SGI	BF200		0
BF274	NS	T0106	L18	25V	25V	4V	50MA	125C	200MWF	400M	OR6	70MN	1MA	TIA	SGI	BF173		0
BF274B	NS	T0106	L18	25V	25V	4V	50MA	125C	200MWF	400M	OR6	100MN	1MA	FRH	SGI	BF173		0
BF274C	NS	T0106	L18	25V	25V	4V	50MA	125C	200MWF	400M	OR6	70/120	1MA	TIA	SGI	BF173		0
BF275	NS	T072	L06	40V	40V	5V	20MA	175C	175MWF	250M	OR8	35MN	2.5MA	VLA	RIZ	BF200	2N4252	2
BF287	NS	T072	L06	40V	40V	4V	20MA	200C	250MWF	400M	DR42	40MN	2MA	FRG	SGI	BF200		0
BF288	NS	T072	L06	40V	40V	4V	20MA	200C	250MWF	250M	DR48	65MN	1MA	FRG	SGI	BF200		0
BF290	NS	T072	L06	40V	40V	4V	20MA	200C	250MWF	700M	DR42	50MN	3MA	TUO	SGI	BF183		0
BF291	NS	T018	L01	50V	40V	5V	100MA	200C	360MWF	260M	3P5	60/300	10MA	VLA	SGI	BFX93	2N918	0
BF291A	NS	T018	L01	50V	40V	5V	100MA	200C	360MWF	260M	3P5	60MN	10MA	VLA	SGI	BFX93	2N918	0
BF291B	NS	T018	L01	50V	40V	5V	100MA	200C	360MWF	260M	3P5	100MN	10MA	VLA	SGI	BFX93	2N918	0
BF292	NS	T039	L04	220V	220V	5V	300MA	200C	800MWF	30M	12P	30MN	10MA	TVH	SGI	BF258		0
BF292A	NS	T039	L04	150V	150V	5V	100MA	200C	800MWF	30M	12P	30MN	10MA	TVM	SGI	BF257		0
BF292B	NS	T039	L04	190V	190V	5V	100MA	200C	800MWF	30M	12P	30MN	10MA	TVH	SGI	BF258		0
BF292C	NS	T039	L04	220V	220V	5V	300MA	200C	800MWF	30M	12P	30MN	10MA	TVH	SGI	BF258		0
BF293	NS	T018	L01	50V	45V	5V	50MA	200C	360MWF	250M	3P5	50/300	10MA	VLA	SGI	BSW64	2N2222A	0
BF293A	NS	T018	L01	50V	45V	5V	50MA	200C	360MWF	190M	5P4	170TP	10MA	VLA	SGI	BSW64	2N2222A	0
BF293D	NS	T018	L01	50V	45V	5V	50MA	200C	360MWF	190M	5P4	100TP	10MA	VLA	SGI	BSW64	2N2222A	0
BF294	NS	T039	L04	160V	160V	5V	100MA	200C	800MWF	40M	3P5	30MN	10MA	TVM	SGI	BF257		0
BF297	NS	X10	L20	160V	160V	5V	100MA	150C	625MWF	95M	10P	30/150	30MA	TVM	TIW	BF257		0
BF298	NS	X10	L20	250V	250V	5V	100MA	150C	625MWF	95M	10P	30/150	30MA	TVH	TIW	BF258		0
BF299	NS	X10	L20	300V	300V	5V	100MA	150C	625MWF	95M	10P	30/150	30MA	TVE	TIW	BF259		0
BF302	NS	T072	L51	40V	30V	4V	50MA	175C	150MWF	325M	DR38	35/125	1MA	TIG	ATI	BF167		0
BF303	NS	T072	L51	40V	30V	3V	50MA	175C	150MWF	250M	DR38	110MN	1MA	FRH	ATI	BF184		0
BF304	NS	T072	L51	40V	30V	4V	50MA	175C	150MWF	250M	DR25	35/120	1MA	FRM	SGI	BF167		0
BF305	NS	T05	L04	180V	150V	5V	50MA	200C	600MWF	50M	3P5	20MN	30MA	TVM	ATI	BF257		0
BF306	NS	T072	L51	40V	25V	4V	25MA	175C	175MWF	500M	DP23	38MN	7MA	TIA	ATI	BF173		0
BF308	NS	T072	L51	40V	35V	4V	50MA	175C	150MWF	800M	DP25	40MN	1MA	ULA	SGI	BFY90	2N2857	0