

| | | | | | | | | |
|---------------|-------------|-------------|--|------------|-----------|----------|-----|--|
| BF 304 | Sgs | Si-N | TV IF, 40/30V, 500MHz, F=3.5dB(1MHz) | 5k | TO-72 | BF 199 | 7d | BF 199, BF 224, BF 311, 2SC2215...16,++ |
| BF 305 | Sgs | Si-N | Vid, 185/150V, 0,1/0,15A, 0,6W, 100MHz | 2a | TO-39 | BF 259 | 2a | BF 258...259, BF 658...659, 2N5058...5059 |
| BF 306 | Sgs | Si-N | TV IF, 40/25V, 1000MHz | 5k | TO-72 | BF 199 | 7d | BF 199, BF 224, BF 311, 2SC2215...16,++ |
| BF 307 | | Si-N | TV IF | 5k | TO-72 | BF 199 | 7d | BF 199, BF 224, BF 311, 2SC2215...16,++ |
| BF 308 | Sgs | Si-N | TV IF, 40/35V, >800MHz | 5k | TO-72 | BF 199 | 7d | BF 199, BF 224, BF 311, 2SC2215...16,++ |
| BF 309 | Sgs | Si-N | TV IF, 40/35V, >800MHz | 5k | TO-72 | BF 198 | 7d | BF 198, BF 225, BF 310, 2SC2215...16,++ |
| BF 310 | Aeg,Sie | Si-N | FM Inp, TV IF, 30/30V, 580MHz | 7a | TO-92 | BF 198 | 7d | BF 198, BF 225, BF 314, 2SC1855...56,++ |
| BF 311 | Aeg,Phi | Si-N | TV IF, 35/25V, 750MHz | 7d | TO-92 | BF 199 | 7d | BF 199, BF 224, 2SC2215...16, 2SC2717,++ |
| BF 314 | Aeg,Sie | Si-N | FM/VHF Inp, 30/30V, 450MHz, F=2dB(100MHz) | 7a | TO-92 | 2SC2570A | 7f | BF 225, BF 496, 2SC1393, 2SC1856,++ |
| BF 315 | Sgs | Si-P | AM/FM, 20/20V, 500MHz, F=3.5dB(1MHz) | 2a | TO-18 | BF 324 | 7a | BF 324, BF 440...441, BF 450...451,++ |
| BF 316(A) | Sgs | Si-P | UHF Mx.Os, 40/35V, 550...600MHz, F=5dB(800MHz) BF316: 550MHz, Gp=11dB, A: 600MHz, Gp=12dB(800MHz) | 5g | TO-72 | | | BF 372, BF 516, BF 606, BFR 38 |
| BF 317 | Sgs | Si-P | =BF 315: | 8a | TO-106 | >BF 315 | | -BF 315 |
| BF 320 | Tix | P-FET | LF,HF, 15V, Idss=0.3...15mA, Up=0.3...7.9V | 7e | TO-92 | | | 2N3820, 2N3909, 2N5800, 2N5462, ++ |
| BF 321(A...F) | Tho | Si-N | Uni, 30/20V, 0,03A, 0,3W | 8a | TO-106 | BC 546 | 7a | BC 168, BC 183, BC 238, BC 548, 2SD767,++ |
| BF 322 | Tix | Si-N | LFS, 30/25V, 0,6A, 0,4W, 250MHz | (BF323) 2a | TO-39 | BC 141 | 2a | BC 140...141, BC 337...338, BC 635, ++ |
| BF 323 | Tix | Si-P | LFS, 30/25V, 0,6A, 0,4W, 250MHz | (BF322) 2a | TO-39 | BC 161 | 2a | BC 160...161, BC 327...328, BC 636, ++ |
| BF 324 | Phi,Sie,++ | Si-P | FM/VHF Inp, 30/30V, 450MHz, F=3dB(100MHz) | 7a | TO-92 | BF 324 | 7a | BF 414, BF 506, BF 914, BF 936, BF 939 |
| BF 325 | Tix | Si-N | TV IF, 50/40V, 700MHz | 7a | SOT-30 | BF 198 | 7d | BF 198, BF 225, BF 310, 2SC2215...16,++ |
| BF 327 | Phi | MOS-N-FET-d | Dual-Gate, VHF, 20V, Idss=20...55mA, Up=1.5...3.8V | 25g | SOT-103 | | | - |
| BF 329 | Sgs | Si-N | TV IF, agc, 40/30V, 730MHz, Gp=26dB(36.6MHz) | 11d | SOT-25 | BF 198 | 7d | BF 198, BF 225, BF 310, 2SC1855, 2SC2215 |
| BF 330 | Sgs | Si-N | TV IF, 40/25V, 1000MHz, Gp=26dB(35MHz) | 11d | SOT-25 | BF 199 | 7d | BF 199, BF 224, BF 311, 2SC2215...16,++ |
| BF 332 | Sgs | Si-N | AM/FM Mx.Os,IF, 30/20V, 600MHz, F=4dB(100MHz) | 11d | SOT-25 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 333 | Sgs | Si-N | AM/FM Mx.Os,IF, 30/20V, 400MHz, F=4dB(100MHz) | 11d | SOT-25 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 334 | Phi | Si-N | AM Inp,Mx.Os,IF, 40/30V, 430MHz, F=1.5dB(200kHz) | 11d | SOT-25 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 335 | Phi | Si-N | FM Inp,Mx.Os,IF, 370MHz, F=2dB(200kHz) | 11d | SOT-25 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 336 | Mot,Phi,Tho | Si-N | Vid, 185/180V, 0,1/0,2A, 0,8W, 130MHz | 2a | TO-39 | BF 259 | 2a | BF 258...259, BF 658...659, 2N5058...5059 |
| BF 336 D | Tix | Si-N | =BF 336: 0,5A, 0,5W | 2a | TO-5 | | | 2SD413, 2SD576, 2SD624 |
| BF 337 | Mot,Phi,Tho | Si-N | =BF 336: 250V | 2a | TO-39 | BF 259 | 2a | BF 258...259, BF 658...659, 2N5058...5059 |
| BF 337 D | Tix | Si-N | =BF 337: 0,5A, 0,5W | 2a | TO-5 | | | 2SD576, 2SD593 |
| BF 338 | Mot,Phi,Tho | Si-N | =BF 336: 300V | 2a | TO-39 | BF 259 | 2a | BF 259, BF 659, BFR 89, 2N5058 |
| BF 338 D | Tix | Si-N | =BF 338: 0,5A, 0,5W | 2a | TO-5 | | | 2SD593 |
| BF 339 | Tix | Si-P | VHF Inp,Mx.Os, 25/18V, 500MHz | 7d | SOT-30 | BF 324 | 7a | BF 324, BF 414, BF 506, BF 914, BF 936 |
| BF 340 | Tix | Si-P | AM Inp,Mx.Os,IF, 35V, >80MHz, F=1dB(1MHz), hFE>30 | 7d | SOT-30 | BF 324 | 7a | BF 324, BF 440...441, BF 450...451,++ |
| BF 341 | Tix | Si-P | =BF 430: hFE=45...150 | 7d | SOT-30 | BF 324 | 7a | BF 324, BF 440...441, BF 450...451,++ |
| BF 342 | Tix | Si-P | =BF 340: hFE=60...150 | 7d | SOT-30 | BF 324 | 7a | BF 324, BF 440...441, BF 450...451,++ |
| BF 343 | Tix | Si-P | =BF 340: hFE>30 | 7d | SOT-30 | BF 324 | 7a | BF 324, BF 440...441, BF 450...451,++ |
| BF 344 | Sgs | Si-N | AM Inp,Mx.Os,IF, 30/20V, 500MHz, F=2dB(1MHz) | 2d | TO-18 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 345 | Sgs | Si-N | AM Inp,Mx.Os,IF, 30/20V, 500MHz, F=2dB(1MHz) | 2d | TO-18 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 346 | Tix | N-FET | VHF, In, 15V, Idss=2...80mA, Up=0.5...5.5V, 500MHz | 7f | SOT-30 | | | BF 256, BFR 71, 2N3822, 2N4416,++ |
| BF 347 | Tix | N-FET | LF,HF, 30V, Idss=0.5...2.5mA, Up<0,5V | 7e | TO-92 | | | BFW 13, 2N4338, 2SK68, 2SK106, 2SK118,++ |
| BF 348 | Tix | N-FET | FM/VHF Inp,Mx, 40V, Idss=10...60mA, Up=1...6V | 7f | TO-92 | | | BF 256, BFR 10, 2N5397, 2N5486 |
| BF 350 | Tix | MOS-N-FET-d | Dual-Gate, VHF, 15V, Idss=3...30mA, Up<5V | 5h | TO-72 | BF 960 | 25g | BF 900, 3SK40 |
| BF 351 | Tix | MOS-N-FET-d | Dual-Gate, VHF, 24V, Idss=5...30mA, Up<5V | 5h | TO-72 | BF 960 | 25g | 3N201...206, 3N209...210, 3N211...213 |
| BF 352 | Tix | MOS-N-FET-d | Dual-Gate, VHF, 24V, Idss=5...30mA, Up<2V | 5h | TO-72 | BF 960 | 25g | BF 963, 3SK51, 3SK74, 3SK81 |
| BF 353 | Tix | MOS-N-FET-d | Dual-Gate, VHF, 24V, Idss=5...30mA, Up<3V | 5h | TO-72 | BF 960 | 25g | BF 963, 3SK51, 3SK74, 3SK81 |
| BF 354 | Tix | MOS-N-FET-d | Dual-Gate, VHF, 24V, Idss=7...15mA, Up>3V | 5h | TO-72 | BF 960 | 25g | BF 963, 3SK41, 3SK74, 3SK81 |
| BF 355 | Phi,Tix | Si-N | Vid, 300/225V, 0,1A, 0,8W, >80MHz | 2a | TO-39 | BF 259 | 2a | BF 259, BF 659, 2N5058 |
| BF 356 | Tix | Si-N | Vid, 220/220V, 0,2A, 0,8W, 100MHz | 7c | TO-92 | BF 420 A | 7c | BF 392...393, BF 420A, BF 422A, MPS-A42,++ |
| BF 357(K,S) | Tix | Si-N | UHF A, 30/15V, 0,05A, 1,6GHz, Gp=7,5dB(800MHz) | 7a | SOT-30 | 2SC2570A | 7f | BF 377...378, BF 689, BF 763, 2SC3776,++ (BF 606, BF 679...680, BF 967...970,++) (BF 606, BF 679...680, BF 967...970,++) |
| BF 359 | Sgs | Si-P | Min, UHF Inp In, 40/35V, 850MHz, F=4dB(800MHz) | (40b) | | | | |
| BF 360 | Sgs | Si-P | Min, UHF Mx.Os, 40/35V, 750MHz, Gp=10dB(800MHz) | (40b) | | | | |
| BF 362 | Aeg,Phi,++ | Si-N | UHF Inp agc, 30/20V, 800MHz, F=5dB(800MHz) | 24a | SOT-37 | 2SC2466 | 25p | 2SC2464...66, 2SC2726, (BF 689K, BF 763)6 |
| BF 363 | Aeg,Phi,++ | Si-N | UHF Mx, 30/20V, 700MHz, Gp=12dB(900MHz) | 24a | SOT-37 | 2SC2466 | 25p | 2SC2464...66, 2SC2726, (BF 689K, BF 763)6 |
| BF 364 | Phi,Tho | Si-N | AM Inp,Mx.Os,IF, 30/20V, 260MHz | 8d | TO-106 | BF 255 | 7d | BF 240, BF 254, BF 494, 2SC829, 2SC2210+ |
| BF 365 | Phi,Tho | Si-N | FM Inp,Mx.Os,IF, 30/20V, 200MHz | 8d | TO-106 | BF 255 | 7d | BF 241, BF 255, BF 495, 2SC829, 2SC2210+ |
| BF 366 | Mot | Si-N | FM/VHF agc, 35/30V, >400MHz, Gp=20dB(200MHz) | 7e, 7f | TO-92 | 2SC2570A | 7f | BF 225, BF 314, BF 496, 2SC1855...56, ++ |
| BF 367 | Mot | Si-N | TV IF, agc, 40/30V, 440MHz, Gp=25dB(35MHz) | 7f | TO-92 | BF 198 | 7d | BF 198, BF 225, BF 310, 2SC1855, 2SC2215 |
| BF 368 | Mot,Mic | Si-N | AM/FM Mx.Os,IF, 25/15V, >250MHz, F=4dB(100MHz) | 7e | TO-92 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 368 K | | Si-N | =BF 368: | 7f | TO-92 | >BF 368 | | -BF 368 |
| BF 369 | Mot,Mic | Si-N | AM/FM Mx.Os,IF, 30/20V, >400MHz, F=4dB(100MHz) | 7e | TO-92 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 369 K | | Si-N | =BF 369: | 7f | TO-92 | >BF 369 | | -BF 369 |
| BF 370(R) | Phi | Si-N | TV IF Inp (OFW/SAW-Filter), 40/15V, >500MHz | 7a | TO-92 | BF 959 | 7d | BF 920...921S, BF 959 |
| BF 371 | Mot | Si-N | TV IF, 40/30V, 100mA, 720MHz | 7f | TO-92 | BF 199 | 7d | BF 199, BF 224, BF 311, 2SC2215...16,++ |
| BF 372 | Mot,Sgs | Si-P | VHF Inp agc, 40/35V, 850MHz, F=2,7dB(200MHz) | 5g | TO-72 | | | BF 506, BF 509, BF 914, BF 939 |
| BF 373 | Mot | Si-N | TV IF, 45/45V, 100mA, 720MHz | 7f | TO-92 | BF 199 | 7d | BF 199, BF 224, BF 311, 2SC2215...16,++ |
| BF 374 | Mot | Si-N | FM/VHF, 30/25V, 100mA, >400MHz, F=4dB(100MHz) | 7f | TO-92 | BF 199 | 7d | BF 225, BF 314, BF 496, 2SC1393, 2SC1856 |
| BF 375 | Mot | Si-N | FM/VHF, 30/25V, 100mA, >400MHz, F=4dB(100MHz) | 7f | TO-92 | BF 199 | 7d | BF 225, BF 314, BF 496, 2SC1393, 2SC1856 |
| BF 377 | Aeg | Si-N | VHF/UHF, 30/15V, >1300MHz, Gp=12dB(800MHz) | 7a | TO-92 | 2SC2570A | 7f | BF 689, BF 763, 2N2857, 2SC3776...77,++ |
| BF 378 | Aeg | Si-N | =BF 377: Gp=14dB(800MHz) | 7d | TO-92 | 2SC2570A | 7f | -BF 377 |
| BF 379 | Aeg,Mot | Si-P | AM/FM, 40/25V, 350MHz, Gp>16dB(200MHz) | 7a | TO-92 | BF 324 | 7a | BF 324, BF 440...441, BF 450...451,++ |
| BF 380 | Mot | Si-N | Vid P, 180/180V, 0,5A, 10W, 90MHz | 13m | (Uniwatt) | MPS-U10 | 13m | MPS-U10, BF 460...462, (BF 757...759)5 |
| BF 381 | Mot | Si-N | =BF 380: 250/250V | 13m | (Uniwatt) | MPS-U10 | 13m | MPS-U10, BF 460...462, (BF 757...759)5 |
| BF 382 | Mot | Si-N | =BF 380: 300/300V | 13m | (Uniwatt) | MPS-U10 | 13m | MPS-U10, BF 461...462, (BF 758...759)5 |
| BF 384 | Tix | Si-N | AM/FM Inp,Mx.Os,IF, 30/20V, 800MHz, F=3dB(60MHz) | 7d | SOT-30 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 385 | Tix | Si-N | AM/FM Inp,Mx.Os,IF, 30/20V, 800MHz, F=3dB(60MHz) | 7d | SOT-30 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 387 | Sgs | Si-N | Vid, 100/100V, 0,05A, 0,8W, 120MHz | 2a | TO-39 | BF 259 | 2a | BF 257...259, BF 657...659, 2N5058...5059 |
| BF 388 | Sgs | Si-N | =BF 387: 160/150V | 2a | TO-39 | BF 259 | 2a | BF 257...259, BF 657...659, 2N5058...5059 |
| BF 389 B | | Si-N | =BF 387: 220V | 2a | TO-39 | BF 259 | 2a | BF 258...259, BF 658...659, 2N5058...5059 |
| BF 389 C | | Si-N | =BF 387: 250V | 2a | TO-39 | BF 259 | 2a | BF 258...259, BF 658...659, 2N5058...5059 |
| BF 390 | Sgs | Si-N | Vid, 310/180V, 0,1A, 0,6W, 120MHz | 2a | TO-39 | BF 259 | 2a | BF 259, BF 659, BFR 89, 2N5058 |
| BF 391(K,L,M) | Mot,Sgs | Si-N | Vid, 200/200V, 0,5A, 0,625W, >50MHz | 7e, 40 | TO-92 | BF 420 A | 7c | BF 420A, BF 422A, BFP 22, MPS-A43 |
| BF 391 P1 | Tho | Si-N | =BF 391: 0,2A, 1W | 30e | TO-237 | MPS-U106 | 13m | (BF 460...461, BF 757...759, MPS-U10,++)5 |
| BF 391 P2 | Tho | Si-N | =BF 391: 0,2A, 1W | 30b | TO-237 | BF 759e | 13h | BF 757...759, (BF 460...461, MPS-U10,++)5 |
| BF 392(K,L,M) | Mot,Sgs | Si-N | =BF 391: 250/250V | 7e, 40 | TO-92 | BF 420 A | 7c | BF 420A, BF 422A, BFP 25, MPS-A42 |
| BF 392 P1 | Tho | Si-N | =BF 392: 0,2A, 1W | 30e | TO-237 | MPS-U106 | 13m | (BF 460...461, BF 757...759, MPS-U10,++)5 |
| BF 392 P2 | Tho | Si-N | =BF 392: 0,2A, 1W | 30b | TO-237 | BF 759e | 13h | BF 757...759, (BF 460...461, MPS-U10,++)5 |
| BF 393(K,L,M) | Mot,Sgs | Si-N | =BF 391: 300/300V | 7e, 40 | TO-92 | BF 420 A | 7c | BF 420A, BFP 25, MPS-A42 |
| BF 393 P1 | Tho | Si-N | =BF 393: 0,2A, 1W | 30e | TO-237 | MPS-U106 | 13m | (BF 461, BF 758...759, MPS-U10,++)5 |
| BF 393 P2 | Tho | Si-N | =BF 393: 0,2A, 1W | 30b | TO-237 | BF 759e | 13h | BF 758...759, (BF 461, MPS-U10,++)5 |
| BF 394 | Mot | Si-N | AM/FM Inp,Mx.Os,IF, 30/30V, 100mA, >80MHz | 7f | TO-92 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 395 | Mot | Si-N | AM/FM Inp,Mx.Os,IF, 30/30V, 100mA, >80MHz | 7f | TO-92 | BF 255 | 7d | BF 240...241, BF 254...255, BF 494...495,++ |
| BF 397 | Tix | Si-P | Nixie, Vid, 90/90V, 0,1A, 0,625W | 7a | SOT-30 | BF 421 A | 7c | BF 435...437, BSS 68, 2SA1370...1371 |