

BY 332	Gie,Mot	Si-Di	=BY 330: 200V	31a	SOD-22	BY 228	31a	BY 201/2, BYX 55/350, RGP 10D...M, ++
BY 333	Gie,Mot	Si-Di	=BY 330: 300V	31a	SOD-22	BY 228	31a	BY 201/3, BYX 55/350, RGP 10G...M, ++
BY 334	Gie,Mot	Si-Di	=BY 330: 400V	31a	SOD-22	BY 228	31a	BY 201/4, BYX 55/600, RGP 10G...M, ++
BY 335	Gie,Mot	Si-Di	=BY 330:	31a	SOD-22	BY 228	31a	BY 201/5, BYX 55/600, RGP 10J...M, ++
BY 336	Gie,Mot	Si-Di	=BY 330: 500V	31a	SOD-22	BY 228	31a	BY 201/5, BYX 55/600, RGP 10J...M, ++
BY 337	Gie,Mot	Si-Di	=BY 330: 800V	31a	SOD-22	BY 228	31a	BY 231/800, BY 245/800, RGP 10K...M, ++
BY 338	Gie,Mot	Si-Di	=BY 330: 1000V	31a	SOD-22	BY 228	31a	BY 231/1000, BY 245/1200, RGP 10M, ++
BY 339	Gie,Mot	Si-Di	=BY 330: 1500V	31a	SOD-22	BY 228	31a	BY 231/1500, BY 228, BY 448
BY 350/....	Sie	Si-Di	FRr, 1300...1500V, 1.5A, <4µs	31a	SOD-64	BY 228	31a	BY 228, BY 448
BY 359/....	Phi	Si-Di	TV FRr, 800/1000...1300/1500V, 6.5/60A, <600ns	17k	TO-220	BY 359/1500	17k	-
BY 359F/....		Si-Di	=BY 359/.... Iso	(Uf<2,3V(20A))	SOT-186	(BY 359/1500) ³	17k	-
BY 360/600	Sie	Si-Di	FRr, 600V, 1A, Uf<1,1V(1A), <400ns	31a	DO-27A	BYW 33 M	31a	BY 201/4, BYX 55/600, RGP 10J...M, ++
BY 396(P)	Itt,Mot,++	Si-Di	TV Rr, 100V, 3A, Uf<1,2V(5A), <500ns	31a	DO-27A	BYW 95 C	31a	BYW 95A...C, BYW 14...16/100, RGP 30B...M++
BY 397(P)	Itt,Mot,++	Si-Di	=BY 396: 200V	31a	DO-27A	BYW 95 C	31a	BYW 95A...C, BYW 14...16/200, RGP 30D...M++
BY 398(P)	Itt,Mot,++	Si-Di	=BY 396: 400V	31a	DO-27A	BYW 95 C	31a	BYW 95B...C, BYW 14...16/400, RGP 30G...M++
BY 399(P)	Itt,Mot,++	Si-Di	=BY 396: 800V	31a	DO-27A	BYW 96 E	31a	BYW 96D...E, BYW 14...16/800, RGP 30K...M++
BY 399 S	Gie	Si-Di	=BY 396: 1000V	31a	DO-27A	BYW 96 E	31a	BY 228, BY 438, BYW 96E RGP 30M
BY 400	Mot	Si-Di	TV Rr, 1300V, 2/15A, Uf<1,3V(3A), <500ns	31a	DO-27	BY 228	31a	BY 228, BY 328, BY 448
BY 401	Mot,Tix	Si-Di	Rr, 50V, 0.5A, Uf<1,1V(0.5A)	31a	DO-7	BA 159	31a	BY 126, BY 135, BY 226, 1N4001...4007, ++
BY 402	Mot,Tix	Si-Di	=BY 401: 100V	31a	DO-7	BA 159	31a	BY 126, BY 134, BY 226, 1N4002...4007, ++
BY 403	Mot,Tix	Si-Di	=BY 401: 200V	31a	DO-7	BA 159	31a	BY 126, BY 134, BY 226, 1N4003...4007, ++
BY 404	Mot,Tix	Si-Di	=BY 401: 400V	31a	DO-7	BA 159	31a	BY 126, BY 134, BY 226, 1N4004...4007, ++
BY 405	Mot,Tix	Si-Di	=BY 401: 600V	31a	DO-7	BA 159	31a	BY 126, BY 134, BY 226, 1N4005...4007, ++
BY 406(A)	Phi,Mot	Si-Di	=BY 206: 0.8A	31a	DO-15	BYD 33 M	31a	BY 201/4, BYX 55/350, RGP 10G...M, ++
BY 407(A)	Phi,Mot	Si-Di	=BY 207: 0.8A	31a	DO-15	BYD 33 M	31a	BY 201/6, BYX 55/600, RGP 10J...M, ++
BY 409(A)	Phi	Si-Di	TV kv-Rr, 11,5/12,5kV, 2,5mA, Uf<36V(0,1A), 400ns	31a	SOD-34	BY 713	31a	BY 209, BY 509, BY 476, BY 710, BY 720++
BY 410	Itt	Si-Di	FRr, Uni, 100V, 1A, Uf<1V(1A), <100ns	31a	DO-7	BYV 27/200	31a	EGP 10B...D, FE 1A...D, BYX 92/...
BY 428	Phi	Si-Di	TV Damper-Diode, hi-def, 1300/1400V, -/4A, <500ns	31a	SOD-64	-	-	-
BY 430F/1000	Phi	Si-Di	FRr, Iso, 800/1000V, 5A, Uf<2,1V(10A), <110ns	17d	SOT-186	-	-	-
BY 431F/1000	Phi	Si-Di	=BY 430F/1000: Uf<3,15V(10A), <85ns	17d	SOT-186	-	-	-
BY 438	Phi	Si-Di	TV Damper-Di, 1200/1200V, -/5A, Uf<1,5V(5A), <1µs	31a	SOD-64	BY 228	31a	BY 228, BY 328, BY 428
BY 448	Aeg,Phi,Gie	Si-Di	TV Damper-Di, 1500/1500V, 2/8A, Uf<1,6V(3A), <20µs	31a	SOD-57	BY 228	31a	BY 228
BY 458	Aeg,Phi,Gie	Si-Di	=BY 448: 1200V	31a	SOD-57	BY 228	31a	BY 228, BY 328, BY 438
BY 459/1500	Phi	Si-Di	CRT FRr, 1500/1300V, 10/100A, <350ns, ...82kHz (f. Multi-sync Monitor)	17k	TO-220	-	-	-
BY 459F/1500		Si-Di	=BY 459/1500: iso	17d	SOT-186	-	-	-
BY 476(A)	Phi	Si-Di	TV kv-Rr, 16/18kV, 2,5mA, Uf<44V(0,1A), 400ns	31a	(28x4mmØ)	BY 713	31a	BY 711...713, BY 721...723
BY 477	Phi	Si-Di	TV kv-Rr, 21/23kV, 2mA, Uf<50V(0,1A), 400ns	31a	(18x4mmØ)	BY 713	31a	BY 713, BY 723
BY 478	Phi	Si-Di	=BY 477: 25/27,5kV	31a	(18x4mmØ)	BY 713	31a	BY 713...714, BY 723...724
BY 500-....	Gie,Mot,Die	Si-Di	TV Rr, 100...800V, 5A, Uf<1,35V(5A), <200ns	31a	DO-27A	BY 500/800	31a	MR 821...826
BY 505	Phi	Si-Di	FRr, 2000/2200V, 0,05A, Uf<8,5V(0,1A), 200ns	31a	SOD-61	BY 203/20	31a	BY 203/20, SHG 2...2,5
BY 509	Phi	Si-Di	TV kv-Rr, 11,5/12,5kV, 4mA, <43V(0,1A), 200ns	31a	SOD-61	BY 713	31a	BY 609...610, BY 619...620, BY 718...719
BY 510	Phi	Si-Di	=BY 509: 17kV	31a	SOD-61	BY 713	31a	BY 610, BY 620
BY 520-10...20	Gie	Si-Di	FRr, 1000...2000V, 0,5A, Uf<1,5V(0,5A), 500ns	31a	DO-41	-	-	BY 268...269, RGP 15-....
BY 527	Phi,Mot	Si-Di	Rr,contrav., 800/1250V, 0,8/12A, Uf<1V(1A), 2,5µs	31a	SOD-57	BY 527	31a	BYW 18/1000, BYW 56, BYW 86, 1N4249
BY 530-....	Gie	Si-Di	Rr, 50...1000V, 3A, Uf<1V(1A), 5µs	31a	DO-27A	BY 255	31a	BY 251...255, BYW 177...1N5400...5408, ++
BY 550-....	Fag, Die	Si-Di	Rr, 50...800V, 5/60A, Uf<1,1V(5A)	31a	DO-27A	BY 500/800	31a	BY 214/... BY 500/... MR 750...760
BY 584	Phi	Si-Di	TV Rr, 1500/1800V, 0,05/0,8A, Uf<8,5V(0,1A), 200ns	31a	SOD-61	BY 203/20	31a	BY 203/20, SHG 1,5...2
BY 588	Phi	Si-Di	TV Rr, Basis-Emitter-Di, 25V, 1,5/10A, Uf<1,6V(3A)	31a	SOD-57	BYW 95 C	31a	BYW 52, BYX 82, GP 15A...M, 1N5391...96, ++
BY 601	Mot	Si-Di	Rr, 50V, 1,5A, Uf<1,15V(1,5A)	31a	DO-15	BY 255, BYD 33M	31a	BY 226...227, BY 251...255, 1N5391...99, ++
BY 602	Mot	Si-Di	=BY 601: 100V	31a	DO-15	BY 255, BYD 33M	31a	BY 226...227, BY 251...255, 1N5392...99, ++
BY 603	Mot	Si-Di	=BY 601: 200V	31a	DO-15	BY 255, BYD 33M	31a	BY 226...227, BY 251...255, 1N5393...99, ++
BY 604	Mot	Si-Di	=BY 601: 400V	31a	DO-15	BY 255, BYD 33M	31a	BY 226...227, BY 252...255, 1N5395...99, ++
BY 605	Mot	Si-Di	=BY 601: 600V	31a	DO-15	BY 255, BYD 33M	31a	BY 226...227, BY 253...255, 1N5397...99, ++
BY 606	Mot	Si-Di	=BY 601: 800V	31a	DO-15	BY 255, BYD 33M	31a	BY 227, BY 254...255, 1N5398...5399, ++
BY 607	Mot	Si-Di	=BY 601: 1000V	31a	DO-15	BY 255, BYD 33M	31a	BY 227, BY 255, BY 350/1300, 1N5399
BY 608	Mot	Si-Di	=BY 601: 1250V	31a	DO-15	BY 255	31a	BY 227, BY 255, BY 350/1300
BY 609	Phi	Si-Di	TV kv-Rr, 12/15kV, 4mA, Uf<50V(0,1A), 200ns	31a(9mm)	SOD-61	BY 713	31a	BY 619...620, BY 710, BY 720
BY 610	Phi	Si-Di	=BY 609: 12/17kV	31a(9mm)	SOD-61	BY 713	31a	BY 620, BY 710...711, BY 720...721
BY 614	Phi	Si-Di	FRr, 2000/2200V, 0,05/0,5A, Uf<6V(0,05A), <300ns	31a	=SOD-57	(BY 203/20)	31a	(BY 203/20, SHG 2,1)
BY 617	Phi	Si-Di	TV kv-Rr, 7,5/9kV, 4mA, Uf<37,5V(0,1A), 100ns	31a	SOD-61	(BY 713)	31a	BY 708...709, BY 717...719
BY 619	Phi	Si-Di	TV kv-Rr, 12/15kV, 4mA, Uf<75V(0,1A), 100ns	31a	SOD-61	BY 713	31a	BY 609...610, BY 710, BY 720
BY 620	Phi	Si-Di	=BY 619: 12/17kV	31a	SOD-61	BY 713	31a	BY 610, BY 710, BY 720
BY 627	Phi	Si-Di	Impatt-Di, contr.av., 1250V, 2/20A, Uf<1,15V(3A)	31a	SOD-81	-	-	-
BY 705	Phi	Si-Di	kv-Rr, 4/5kV, 20mA, Uf<21V(0,1A), 200ns	31a(5mm)	=SOD-61	-	-	BY 715, CY 5, HS 6
BY 706	Phi	Si-Di	=BY 705: 5/6kV	31a(5mm)	=SOD-61	-	-	BY 716, CY 6, HS 6
BY 707	Phi	Si-Di	TV kv-Rr, 9/10kV, 4mA, Uf<52V(0,1A), 200ns	31a(9mm)	=SOD-61	BY 713	31a	BY 609...610, BY 619...620, BY 717...719
BY 708	Phi	Si-Di	TV kv-Rr, 10/12kV, 4mA, Uf<52V(0,1A), 200ns	31a(9mm)	=SOD-61	BY 713	31a	BY 609...610, BY 619...620, BY 718...719
BY 709	Phi	Si-Di	TV kv-Rr, 12/14kV, 4mA, Uf<52V(0,1A), 200ns	31a(9mm)	=SOD-61	BY 713	31a	BY 609...610, BY 619...620, BY 719
BY 710	Phi	Si-Di	TV kv-Rr, 14/17kV, 3mA, Uf<70V(0,1A), 200ns	31a(11mm)	=SOD-61	BY 713	31a	BY 610, BY 620, BY 711...714, BY 720...724
BY 711	Phi	Si-Di	TV kv-Rr, 16/19kV, 3mA, Uf<70V(0,1A), 200ns	31a(11mm)	=SOD-61	BY 713	31a	BY 712...714, BY 721...724
BY 712	Phi	Si-Di	TV kv-Rr, 18/22kV, 3mA, Uf<76V(0,05A), 200ns	31a(12mm)	=SOD-61	BY 713	31a	BY 713...714, BY 722...724
BY 713	Phi	Si-Di	TV kv-Rr, 20/24kV, 3mA, Uf<76V(0,05A), 200ns	31a(12mm)	=SOD-61	BY 713	31a	BY 714, BY 723...724
BY 714	Phi	Si-Di	TV kv-Rr, 24/30kV, 3mA, Uf<76V(0,05A), 200ns	31a(12mm)	=SOD-61	-	-	BY 724
BY 715	Phi	Si-Di	kv-Rr, 4/5kV, 20mA, Uf<28V(0,1A), 100ns	31a(5mm)	=SOD-61	-	-	BY 705, CY 5, HS 6
BY 716	Phi	Si-Di	=BY 705: 5/6kV	31a(5mm)	=SOD-61	-	-	BY 706, CY 6, HS 6
BY 717	Phi	Si-Di	TV kv-Rr, 9/10kV, 4mA, Uf<69V(0,1A), 100ns	31a(9mm)	=SOD-61	BY 713	31a	BY 609...610, BY 619...620, BY 707...709
BY 718	Phi	Si-Di	TV kv-Rr, 10/12kV, 4mA, Uf<69V(0,1A), 100ns	31a(9mm)	=SOD-61	BY 713	31a	BY 609...610, BY 619...620, BY 708...709
BY 719	Phi	Si-Di	TV kv-Rr, 12/14kV, 4mA, Uf<69V(0,1A), 100ns	31a(9mm)	=SOD-61	BY 713	31a	BY 609...610, BY 619...620, BY 709
BY 720	Phi	Si-Di	TV kv-Rr, 14/17kV, 3mA, Uf<92V(0,1A), 100ns	31a(11mm)	=SOD-61	BY 713	31a	BY 610, BY 620, BY 710...714
BY 721	Phi	Si-Di	TV kv-Rr, 16/19kV, 3mA, Uf<92V(0,1A), 100ns	31a(11mm)	=SOD-61	BY 713	31a	BY 711...714
BY 722	Phi	Si-Di	TV kv-Rr, 18/22kV, 3mA, Uf<88V(0,05A), 100ns	31a(12mm)	=SOD-61	BY 713	31a	BY 712...714
BY 723	Phi	Si-Di	TV kv-Rr, 20/24kV, 3mA, Uf<88V(0,05A), 100ns	31a(12mm)	=SOD-61	BY 713	31a	BY 713...714
BY 724	Phi	Si-Di	TV kv-Rr, 24/30kV, 3mA, Uf<88V(0,05A), 100ns	31a(12mm)	=SOD-61	-	-	BY 714
BY 2000	Die	Si-Di	kv Rr, 2kV, 3/20A, Uf<1,1V(3A)	31a	DO-27A	-	-	-
BY 4000	Die	Si-Di	kv Rr, 4kV, 1,5/10A, Uf<2,1V(1,5A)	31a	DO-27A	-	-	-
BY 6000	Die	Si-Di	kv Rr, 6kV, 1/6A, Uf<3,2V(1A)	31a	DO-27A	-	-	-
BYD...BYR								
BYD 11 D...M	Phi	Si-Di	Rr, contr.av., 200...1000V, 0,58A, Uf<1,2V(1A) D=200V, G=400V, J=600V, K=800V, M=1000V	31a	DO-35	BYD 33 M	31a	BYD 33D...M, BYW 26B...E, 1N4245...49
BYD 13 D...M	Phi	Si-Di	Rr, contr.av., 200...1000V, 1,4/5,5A, Uf<1,05V(1A) D=200V, G=400V, J=600V, K=800V, M=1000V	31a	SOD-81	BYD 33 M	31a	BYD 33D...M, BYW 52...56, 1N5060...5062