

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
40325	NS	T03	L05	35V	35V	5V	15A	200C	117WC			12/60	8A	AHG	RCU	BDY20	2N3055	0
40326	NS	T05	L04		40V	2V5	700MA	200C	1WF			40/200	10MA	AMG	RCU	BFY50	2N2297	0
40327	NS	T05	L04	300V		5V	1A	200C	1WF			40/250	20MA	AME	RCU	BUY60	2N3439	0
40328	NS	T066	L43	300V		6V	2A	200C	35WC			1A	AHE	RCU		2N6235	0	0
40346	NS	T05	L04	175V	100V	4V	1A	200C	1WF	10M		25MN	10MA	AME	RCU	BUY60	2N3439	0
40346V1	NS		L04	175V	100V	4V	1A	200C	1WF	10M		25MN	10MA	AME	RCU			0
40346V2	NS	T05F	L44	175V	100V	4V	1A	200C	1WF	10M		25MN	10MA	AME	RCU			0
40347	NS	T05	L04	60V	40V	7V	1500MA	200C	1WF			25/100	450MA	AMG	RCU	BFY50	2N2297	0
40347V1	NS		L04	60V	40V	7V	1500MA	200C	4WC			25/100	450MA	AMG	RCU			0
40347V2	NS	T05F	L44	60V	40V	7V	1500MA	200C	11WC			25/100	450MA	AMG	RCU			0
40348	NS	T05	L04	90V	65V	7V	1500MA	200C	1WF			30/100	300MA	AHG	RCU	BFY50	2N2297	0
40348V1	NS		L04	90V	65V	7V	1500MA	200C	5WF			30/100	300MA	AHG	RCU			0
40348V2	NS	T05F	L44	90V	65V	7V	1500MA	200C	12WC			30/100	300MA	AHG	RCU		2N2197	0
40349	NS	T05	L04	160V	140V	7V	1500MA	200C	1WF			25/100	150MA	AME	RCU	BSW67	2N5082	0
40349V1	NS		L04	160V	140V	7V	1500MA	200C	1WF			25/100	150MA	AME	RCU			0
40349V2	NS	T05F	L44	160V	140V	7V	1500MA	200C	1WF			25/100	150MA	AME	RCU			0
40350	NS	T072	L06	35V			25MA	175C	180MWF			40MN	2MA	ULA	OBS	BFX73	2N918	0
40351	NS	T072	L06	35V			25MA	175C	180MWF			40FG	2MA	ULA	OBS	BFX73	2N918	0
40352	NS	T072	L06	35V			25MA	175C	180MWF			27MN	2MA	ULA	OBS	BFX73	2N918	0
40354	NS	T018	L01		150V	5V	50MA	175C	500MWF	50M	3P5	55TP	10MA	TVM	RCU	BF257		0
40355	NS				150V	5V	50MA	175C	1WF	50M	3P5	55TP	10MA	TVM	RCU			0
40360	NS	T05	L04		70V	4V	700MA	200C	1WF	50M		40/200	10MA	AMH	RCU	BSW66	2N4001	0
40361	NS	T05	L04	70V		4V	700MA	200C	1WF	50M		75/350	50MA	AMG	RCU	BFY50	2N2297	0
40362	PS	T05	L04	70V		4V	700MA	200C	1WF			35/200	50MA	AMG	RCU	BF595	2N4036	0
40363	NS	T03	L05	70V		4V	15A	200C	115WC	350K		20/70	4A	AHG	RCU	BDY20	2N3055	0
40364	NS	T066	L44	60V		4V	7A	200C	35WC	8M		35/175	500MA	AHG	RCU	BDY79	2N3738	0
40366	NS	T05	L04	120V	65V	7V	1A	200C	1WF			40/120	150MA	AMH	RCU	BSW66	2N4001	0
40367	NS	T05	L04	100V	55V	12V	1500MA	200C	1WF			35/100	200MA	AHG	RCU	BFY50	2N2297	0
40368	NS	T08	L12	100V	55V	12V	3A	200C	25WC	1M		35/100	750MA	AHG	RCB		2N1486	0
40369	NS	T08	L12	100V	55V	12V	3A	200C	25WC	1M		35/100	750MA	AHG	RCB		2N1490	1
40372	NS		L43	90V	55V	7V	4A	200C	6WF	800K		25/100	500MA	AHG	RCU			0
40373	NS		L43	160V	140V	7V	4A	200C	6WF			20/80	500MA	AHE	RCU			0
40374	NS		L43	250V	175V	6V	5A	200C	15WF	15M	120P	40MN	100MA	RHH	RCU			0
40375	NS		L43	120V	50V	7V	7A	200C	6WF	60M	175P	50/200	500MA	AHG	RCU			0
40385	NS	T05	L04	450V	350V	7V	1A	200C	1WF	15M	10P	40/160	20MA	RME	RCU	BUY60	2N3439	0
40389	NS		L04	60V	40V		700MA	200C	1WF	100M	15P	50/250	150MA	AHG	RCU	BFY50	2N3053	0
40390	NS		L04	300V	250V		1A	200C	3W5A	15M	10P	40/160	20MA	AME	RCU	BUY60	2N3439	0
40391	PS		L04	60V	40V	7V	1A	200C	3W5C	60M		50/250	150MA	RMG	RCU	BF595	2N4036	0
40392	NS	T05F	L44	60V	40V	5V	700MA	200C	7WC	100M	15P	50/250	150MA	AMG	RCU	2N2197		0
40394	PS	T05F	L44	60V	40V	7V	1A	200C	1WF	60M	30P	50/250	150MA	AMG	RCU	BFS95	2N4036	0
40397	NS	T018	L01	25V	25V	7V5	200MA	175C	500MWF	50M	20P	165MN	10MA	AMG	RCU	BSX33	2N731	0
40398	NS	T018	L01	25V	25V	7V5	200MA	175C	500MWF	50M	20P	75/300	10MA	AMG	RCU	BSX33	2N731	0
40399	NS	T018	L01	18V	18V	7V	200MA	175C	500MWF	25M	20P	165MN	10MA	RMG	RCU	BSX33	2N731	0
40400	NS	T018	L01	18V	18V	7V	200MA	175C	500MWF	25M	20P	75/300	10MA	RMG	RCU	BSX33	2N731	0
40403	PG	T05	L04	30V		20V	200MA	85C	200MWF			15MN		AMG	OBS	ACY17	2N1188	0
40404	NS	T046	L01	40V		5V		175C	1WF			25MN	10MA	AMG	OBS	BSX33	2N731	0
40405	NS	T046	L01	40V	16V	5V	500MA	200C	300MWF	300M	3P5	20MN	50MA	RMG	RCU	BSW64	2N2222A	0
40406	PS	T05	L04		50V	4V	700MA	200C	1WF	50M		30/200	100UA	ALN	RCU	BF595	2N4036	0
40407	NS	T05	L04		50V	4V	700MA	200C	1WF	50M		40/200	1MA	ALG	RCU	BFY50	2N2297	0
40408	NS	T05	L04		90V	4V	700MA	200C	1WF	50M		40/200	10MA	AMH	RCU	BSW66	2N4001	0
40409	NS		L04	90V		4V	700MA	200C	3WF	50M		50/250	150MA	AMH	RCU	BSW66	2N4001	0
40410	PS		L04	90V		4V	700MA	200C	3WF	50M		50/250	150MA	AMH	RCU	BFR23	2N4929	0
40411	NS	T03	L05	90V		4V	30A	200C	150WC	400K		35/100	4A	AHG	RCU	BDX40	2N3772	0
40412	NS	T05	L03	250V	150V	3V	1A	200C	1WF	10M	10P	40MN	30MA	AME	RCU	BUY60	2N3439	0
40412V1	NS		L03	250V	150V	3V	1A	200C	4WF	10M	10P	40MN	30MA	AME	RCU			0
40412V2	NS	T05F	L44	250V	150V	3V	1A	200C	1WF	10M	10P	40MN	30MA	AME	RCU	BUY60	2N3439	0
40413	NS	T072	L06	35V	20V	3V		200C	200MWF	700M	1P5	30/200	2MA	ULG	RCU	BFY90	2N2857	0
40414	NS	T072	L06	30V	15V	2V5	40MA	200C	200MWF	1G	1P	30/150	3MA	ULG	RCU	BFY90	2N2857	0
40421	PG	T03	L05	75V	50V	1V5	5A	100C	50WC	2M		62/175	1A	RHG	RCU	AL103	2N1906	0
40422	NS	T066	L43	300V		2V	150MA	150C	8WC	25M		50/250	50MA	RME	OBS		2N3739	0
40423	NS		L43	300V		2V	150MA	150C	3W8F	25M		50/250	50MA	RME	OBS		2N3739	0
40424	NS	T066	L43	300V		2V	150MA	150C	8WC	25M		30/150	50MA	RME	OBS		2N3739	0
40425	NS		L43	300V		2V	150MA	150C	3W8F	25M		30/150	50MA	RME	OBS		2N3739	0
40426	NS	T066	L43	300V		2V	150MA	150C	8WC	25M		20/100	50MA	RME	OBS		2N3739	0
40427	NS		L43	300V		2V	150MA	150C	3W8F	25M		20/100	50MA	RME	OBS		2N3739	0
40439	PG	T03	L05	320V		2V	10A	85C	40WC			15MN	6A	RHE	RCU	AU106	2N5155	0
40440	PG	T03	L05	200V		2V	10A	85C	40WC			15MN	6A	RHE	RCU	AU106	2N5155	0
40444	NS	T03	L05	120V		7V	20A	200C	140WC			20MN	5A	AHH	OBS	BDX50	2N3773	0
40457	NS	T018	L01	25V	25V	7V	1A	175C	500MWF	80M	20P	60MN	600MA	RMG	OBS	BSX33	2N731	0
40458	NS	T046	L01	60V	40V	8V	1A	175C	500MWF	150M	20P	50MN	300MA	RMG	RCU	BSX33	2N731	0
40459	NS		L01	60V	40V	8V	1A	175C	1WF	100M		100MN	10MA	RMG	OBS	BSX33	2N731	0
40462	PG	T03	L05	40V	40V	5V	5A	100C	50WC	300K		50MN	1A	AHG	RCU	ASZ16	2N1536	0
40464	NS	T03	L05	35V	35V	4V	5A	150C	40WC	2M		30/170	2A	AHG	OBS	BDY20	2N3055	0
40465	NS	T03	L05	40V	40V	4V	5A	150C	40WC	2M		50/170	2A	AHG	OBS	BDY20	2N3055	0
40466	NS	T03	L05	50V	50V	4V	5A	150C	40WC	2M		50/170	2A	AHG	OBS	BDY20	2N3055	0