



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089
<http://www.nteinc.com>

NTE1082 Integrated Circuit FM IF Amplifier

Description:

The NTE1082 is a silicon monolithic integrated circuit intended for use as a three-stage FM IF amplifier having exceptionally high voltage gain and limiting characteristics. From pin 1 the stabilized voltage can be applied to the mixer stage.

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Supply Voltage, V_{CC} 15V
 Input Voltage, V_{IN} $\pm 3.0\text{V}$
 Power Dissipation, P_D 300mW
 Operating Temperature Range, T_{opr} -20° to $+75^\circ\text{C}$
 Storage Temperature Range, T_{stg} -40° to $+125^\circ\text{C}$

Electrical Characteristics: ($T_A = +25^\circ\text{C}$, $V_{CC} = 10\text{V}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Circuit Current	I_{CC}	DC Current	8.0	12.5	17.0	mA
Output Current	I_{OUT}		0.9	1.6	2.3	mA
Input Voltage	V_I		4.4	5.1	5.8	V
Voltage Gain	A_V	$f = 10.7\text{MHz}$, $R_G = 50\Omega$, $R_L = 1\text{k}\Omega$, $V_I = 40\text{dB}$	60	66	72	dB
Input Resistance	R_{IN}	$f = 10.7\text{MHz}$	-	10	-	$\text{k}\Omega$
Input Capacitance	C_{IN}		-	5	-	pF
Output Resistance	R_{OUT}		-	30	-	$\text{k}\Omega$
Output Capacitance	C_{OUT}		-	3	-	pF

Pin Connection Diagram

