

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
9013	NS	T092	L14	25V	25V	3V	400MA	135C	400MWF			64/202	50MA	AMG	HIN	BC387	2N4401	2
90130	NS	T092	L14	25V	25V	3V	400MA	135C	400MWF			64/91	50MA	AMG	HIN	BC387	2N4401	2
9013E	NS	T092	L14	25V	25V	3V	400MA	135C	400MWF			78/112	50MA	AMG	HIN	BC387	2N4401	2
9013F	NS	T092	L14	25V	25V	3V	400MA	135C	400MWF			96/135	50MA	AMG	HIN	BC387	2N4401	2
9013G	NS	T092	L14	25V	25V	3V	400MA	135C	400MWF			118MN	50MA	AMG	HIN	BC387	2N4401	2
9013H	NS	T092	L14	25V	25V	3V	400MA	135C	400MWF			144MN	50MA	AMG	HIN	BC387	2N4401	2
9015	PS	T092	L14	20V	18V	3V	100MA	135C	310MWF	70M	5P	60MN	1MA	ALN	HIN	BC352B	2N5087	2
9015A	PS	T092	L14	20V	18V	3V	100MA	135C	310MWF	70M	5P	60/150	1MA	ALN	HIN	BC352B	2N5087	2
9015B	PS	T092	L14	20V	18V	3V	100MA	135C	310MWF	70M	5P	100MN	1MA	ALN	HIN	BC352B	2N5087	2
9015C	PS	T092	L14	20V	18V	3V	100MA	135C	310MWF	70M	5P	200MN	1MA	ALN	HIN	BC352B	2N5087	2
9015D	PS	T092	L14	20V	18V	3V	100MA	135C	310MWF	70M	5P	400MN	1MA	ALN	HIN	BC352B	2N5087	2
9016	NS	T092	L14	20V	20V	3V	50MA	135C	310MWF	300M	1P6	28/198	1MA	FVG	HIN	BF369		2
9016D	NS	T092	L14	20V	20V	3V	50MA	135C	310MWF	300M	1P6	28/45	1MA	FVG	HIN	BF369		2
9016E	NS	T092	L14	20V	20V	3V	50MA	135C	310MWF	300M	1P6	39/60	1MA	FVG	HIN	BF369		2
9016F	NS	T092	L14	20V	20V	3V	50MA	135V	310MWF	300M	1P6	54/80	1MA	FVG	HIN	BF369		2
9016G	NS	T092	L14	20V	20V	3V	50MA	135C	310MWF	300M	1P6	72/108	1MA	FVG	HIN	BF369		2
9016H	NS	T092	L14	20V	20V	3V	50MA	135C	310MWF	300M	1P6	97/146	1MA	FVG	HIN	BF369		2
9016I	NS	T092	L14	20V	20V	3V	50MA	135C	310MWF	300M	1P6	132MN	1MA	FVG	HIN	BF369		2
40022	PG	T03	L05	32V		5V	5A	100C	12WC	150K		38MN	1A	AHG	RCU	ASZ16	2N1536	0
40050	PG	T05	L05	40V		5V	5A	100C	12WC	250K		50MN	1A	AHG	RCU	ASZ16	2N1536	0
40051	PG	T03	L05	50V		5V	5A	100C	12WC	250K		50MN	1A	AHG	RCU	ASZ16	2N1536	0
40084	NS	T018	L01	60V	40V	5V	1A	200C	500MWF	100M	15P	50/250	150MA	AHG	RCU	BSX33	2N731	0
40217	NS	T046	L01	25V		3V		175C	300MWF	200M	10P	20MN	10MA	ALG	OBS	BC107	A157	0
40218	NS	T046	L01	25V		5V	50MA	175C	300MWF	200M	5P	20MN	10MA	ALG	OBS	BC107		0
40219	NS	T046	L01	40V	15V	5V		200C	360MWF	300M	6P	30MN	10MA	ALG	OBS	BC107		0
40220	NS	T046	L01	40V		5V	200MA	175C	300MWF	350M	4P	25MN	10MA	RMS	OBS	BSW64	2N2222A	0
40221	NS	T046	L01	40V	15V	5V		200C	360MWF	250M	5P	30MN	10MA	RMS	OBS	BSX20	2N2369	0
40222	NS	T046	L01	25V		3V	200MA	175C	300MWF	200M		20MN	10MA	RMS	OBS	BSX20	2N2369	0
40231	NS	T018	L01	18V	18V	5V	100MA	175C	500MW	30M	44P	55/180	2MA	ALN	RCU	BC107		0
40232	NS	T018	L01	18V	18V	5V	100MA	175C	500MWF	30M	44P	90/300	2MA	ALN	RCU	BC107		0
40233	NS	T018	L01	18V	18V	5V	100MA	175C	500MWF	30M	44P	90/300	2MA	ALN	RCU	BC109	2N930	0
40234	NS	T018	L01	18V	18V	5V	100MA	175C	400MWF	30M	44P	35/180	2MA	ALN	RCU	BC107		0
40235	NS	T072	L06	45V		4V5	50MA	175C	180MWF	500M	OP65	40/170	1MA	TUG	RCU	BF180		0
40236	NS	T072	L06	45V		4V5	50MA	175C	180MWF	500M	OP65	40/275	1MA	TUJ	RCU	BF182		0
40237	NS	T072	L06	45V		4V5	50MA	175C	180MWF	500M	OP65	27/275	1MA	TUO	RCU	BF183		0
40238	NS	T072	L06	45V		4V5	50MA	175C	180MWF	400M	OP65	40/170	1MA	TIA	RCU	BF173		0
40239	NS	T072	L06	45V		4V5	50MA	175C	180MWF	400M	OP65	27/100	1MA	TIG	RCU	BF167		0
40240	NS	T072	L06	45V		4V5	50MA	175C	180MWF	400M	OP65	27/275	1MA	TIG	RCU	BF167		0
40242	NS	T072	L06	45V		4V5	50MA	175C	180MWF	OP65		40/170	1MA	FVG	RCU	BF200		0
40243	NS	T072	L06	45V		4V5	50MA	175C	180MWF	IR35		40/170	1MA	FRM	RCU	BF185		0
40244	NS	T072	L06	45V		4V5	50MA	175C	180MWF		OP8	27/170	1MA	FRM	RCU	BF185		0
40245	NS	T072	L06	45V		4V5	50MA	175C	180MWF	IR5		70/275	1MA	FRH	RCU	BF184		0
40246	NS	T072	L06	45V		4V5	50MA	175C	180MWF	IR5		27/90	1MA	FRM	RCU	BF185		0
40250	NS	T066	L43	50V	40V	5V	4A	200C	29WC			25/100	1500MA	AHG	RCU	BUY38	2N3054	0
40250V1	NS	T066	L43	50V	40V	5V	4A	200C	6WC			25/100	1500MA	AHG	RCU			0
40251	NS	T03	L05	50V	40V	5V	15A	200C	117WC			15/60	8A	AHG	RCU	BDY20	2N3055	0
40253	PG	T01	L02	25V	25V	2V5	500MA	90C	125MWF	500K		50MN	400MA	AMG	OBS	AC128	2N2706	0
40254	PG	T03	L05	32V		5V	5A	100C	12WC	150K		38MN	1A	AHG	RCU	ASZ16	2N1536	0
40255	NS	T05F	L44	450V	350V	7V	1A	200C	10WC	20M		40/160	20MA	TVM	OBS	BF258		0
40256	NS	T05F	L44	300V	250V	7V	1A	200C	10WC	20M		40/160	20MA	TVM	OBS	BF257		0
40261	PG	T01	L02	50V		0V5	10MA	85C	80MWF	20M	3P7	80TP	1MA	VLG	OBS	AF124	2N991	0
40262	PG	T01	L02	50V		0V5	10MA	85C	80MWF	20M	3P7	80TP	1MA	VLG	OBS	AF124	2N991	0
40263	PG	T01	L02	20V		2V5	50MA	100C	120MWF			160TP	1MA	ALG	OBS	AC125	2N406	0
40264	NS	OBS	OBS	300V	300V	7V	100MA	150C	4WC	12M		30/150	50MA	AME	OBS	BF337	2N4927	0
40269	PG	T05	L04	25V		12V	100MA	85C	150MWF			50MN	12MA	ALG	OBS	ACY17	2N1188	0
40283	NS	T046	L01	60V	30V	5V		200C	400MWF	250M	10P	10MN	500MA	RMG	OBS	BSW64	2N2222A	0
40294	NS	T072	L06	30V	15V	2V5	40MA	200C	200MWF	1G	1P	30/150	3MA	ULA	RCU	BFY90	2N2857	0
40295	NS	T072	L06	35V	20V	3V		200C	200MWF	700M	1P5	30/200	2MA	ULA	RCU	BFY90	2N2857	0
40296	NS	T072	L06	30V		2V5	40MA	200C	200MWF			30MN	1MA	VLG	OBS	BFY90	2N2857	0
40309	NS	T05	L04		18V	2V5	700MA	200C	1WF	50M		70/350	50MA	AMG	RCU	BFY50	2N2297	0
40310	NS	T066	L43		35V	2V5	4A	200C	29WC			20/120	1A	AHG	RCU	BUY38	2N3054	0
40311	NS	T05	L04		30V	2V5	700MA	200C	1WF	50M		75/350	50MA	AMG	RCU	BFY50	2N2297	0
40312	NS	T066	L43	60V		2V5	4A	200C	29WC	375K		20/120	1A	AHG	RCU	BUY38	2N3054	0
40313	NS	T066	L43	300V		2V5	2A	200C	35WC			40/250	100MA	AHE	RCU			0
40314	NS	T05	L04		40V	2V5	700MA	200C	1WF	50M		35/150	50MA	AMG	RCU	BFY50	2N2297	0
40315	NS	T05	L04		35V	2V5	700MA	200C	1WF	50M		70/350	50MA	AHG	RCU	BFY50	2N2297	0
40316	NS	T066	L43		40V	5V	4A	200C	29WC	375K		20/120	1A	AHG	RCU	BUY38	2N3054	0
40317	NS	T05	L04		40V	2V5	700MA	200C	1WF			40/200	10MA	AHG	RCU	BFY50	2N2297	0
40318	NS	T066	L43	300V	150V	6V	2A	200C	35WC			50MN	500MA	ALN	RCU	BDY72	2N3441	0
40319	PS	T05	L04		40V	2V5	700MA	200C	1WF	50M		35/200	50MA	RMG	RCU	BFS95	2N4036	0
40320	NS	T05	L04		40V	2V5	700MA	200C	1WF			40/200	10MA	AHG	RCU	BFY50	2N2297	0
40321	NS	T05	L04		300V	5V	1A	200C	1WF			25/200	20MA	AME	RCU	BUY60	2N3439	0
40322	NS	T066	L43		300V	6V	2A	200C	35WC			75MN	500MA	AHE	RCU	2N6235		0
40323	NS	T05	L04		18V	2V5	700MA	200C	1WF	50M		70/350	50MA	AMG	RCU	BFY50	2N2297	0
40324	NS	T066	L43		35V	2V5	4A	200C	29WC	375K		20/120	1A	AHG	RCU	BUY38	2N3054	0