

# Product Detail Page



25  
W MAX

115  
dB

## TM-25

Number: 17.0970

### Attention guaranteed!

With our range of reliable megaphones, we provide the perfect solution for each application. A few basic selection criteria will help you to choose the right unit. The operating range is surely the most important one. Here, the following applies: with increasing sound pressure (in dB), the operating range of the megaphone increases, too. Furthermore, it is possible to choose between megaphones with integrated microphone, with hand-held microphone or units with an additional wireless microphone. Each megaphone from MONACOR is supplied with power by standard batteries. As an alternative, a few units also feature a 12V connection. Size, weight and the power supply are further selection criteria for choosing the right megaphone. With these comparison criteria, you will surely find the ideal megaphone meeting your individual requirements very quickly. **Megaphone**

- Built-in microphone
- Siren, switchable
- Jack for external 12V battery operation
- Volume control
- Connection cable for motor vehicles



## Technical Facts

<b>Built-in microphone</b>	X
<b>Hand-held microphone</b>	-
<b>Wireless microphone</b>	-
<b>Lockable button microphone</b>	-
<b>Pistol grip</b>	X
<b>Carrying strap</b>	-
<b>Wrist strap</b>	X
<b>Shoulder strap</b>	-
<b>Connection cable for motor vehicles</b>	X
<b>Siren</b>	X
<b>Acoustic signal</b>	-
<b>Volume control</b>	X
<b>Battery status indication</b>	-
<b>8mm thread</b>	-
<b>Aux input with level control</b>	-
<b>Output power</b>	25W <sub>MAX</sub>
<b>SPL (1W/1m)</b>	115dB
<b>Power supply</b>	8 x 1.5V batt. C size not supplied, ext. 12V = /2A
<b>12V connection</b>	X
<b>Dimensions</b>	Ø 230mm x 370mm
<b>Weight</b>	1.7kg

